

Helical Antenna with Universal FME-Connection System
for Portable Equipment in the 27 MHz Band

BESCHREIBUNG

- Flexible, conical steel helix moulded in thermoplastic rubber.
- Significant reduction of length due to the helical principle.
- Optimum performance compared to physical dimensions.
- Delivered factory tuned and tested to ensure minimum VSWR.
- Provided with universal FME-connection system for optimum flexibility and easily exchangeable connectors.
- Designed for use with the following of Procoms line of black FME-connectors (to be ordered separately): BFME-UHF, BFME-BNC, BFME-TNC, BFME-N, BFME-EBNC and BFME-ETNC.



SPEZIFIKATIONEN

Elektrisch DE	
Modell	HX 27 1/4-FME
Frequenz	27 MHz CB band
Antennentyp	Gekürzte ¼ λ Helixantenne für tragbare Anwendungen
Max. Eingangsleistung	10 W
Polarisation	Vertikal
Impedanz	50 Ω
VSWR	< 3.0:1 bei direkter Montage auf dem tragbaren Gerät
Mechanisch DE	
Anschlusstyp	FME(f) (Auswechselbare BFME-Adapter separat zu bestellen)
Materialien	Stahlwendel in thermoplastischem Gummi schwarz verchromtes Messing
Farbe	Schwarz
Höhe	ca. 290 mm
Gewicht	ca. 0.045 kg

BITTE BEACHTEN

Die HX 27 1/4 ist ebenfalls mit verschiedenen, fest montierten Gewindeanschlüssen (ohne FME-Adaptersystem) verfügbar. Informationen für diese speziellen Versionen auf Anfrage.

BESTELLUNG

Modell	Produkt Nr
HX 27 1/4-FME(f)	140000043

EMPFOHLENE BFME-ADAPTER

BFME-UHF	BFME-BNC	BFME-TNC	BFME-N
BFME-EBNC		BFME-ETNC	

(separat zu bestellen)